

# PTZ Broadcaster Keyboard



Enjoy the multiple options and advanced features of the **PTZ Broadcaster Keyboard**. It is compatible with the VISCA, ONVIF and PELCO protocols, as well as with all Square One Cameras.

The built in web servers makes the configuration interface simple, clear and easy to operate. It only takes a few steps to achieve perfect control of the video conferencing camera. It can be used in houses of worship, conference facilities, live events and broadcast markets.



Support network and analog two control modes, have independent IP addresses in network mode.



Support VISCA, VISCA over IP, Onvif, PELCO-P, PELCO-D protocols, and VISCA is fully compatible.



Support software function control of conference cameras.



Adopt high-quality variable speed 4D joystick control, comfortable operations. Omnidirectional movements.



Support up to 50 cameras, with 4 shortcut control buttons for quick and easy operation.

# PTZ Broadcaster Keyboard Technical Specifications

## FEATURES

Operation system	Linux
Protocol	VISCA, VISCA over IP, Onvif, PELCO-P, PELCO-D
Interface	RS422, RS232, RJ45
Warning Tone	Key-touch beep on/off
LCD Display	TFT LCD 320*240
Power Consumption	≤5W
Power supply	DC12V-2A
Working temperate	10°C ~ 55°C / 14°F~131°F
Storage temperature	10°C ~ 60°C / 14°F~140°F
Dimension	321.6mm x 179.2mm x 105.7mm
Weight	1290g

**The SQ PTZ Controller can be used in conference rooms, houses of worship and for live events.**



**SQUARE ONE**

call +44 1273 455552

Unit 3, Northbrook Business Park, Northbrook Rd, Worthing BN14 8PQ

Copyright Technical Solutions Ltd 2022